




**4-PORT UNIVERSAL
GaN SUPER CHARGER**

COMPATIBLE IN 150+ COUNTRIES

MODEL: P100WPDBK

PRODUCT OVERVIEW



- 1 Multi-socket
- 2 US/AU/UK/EU Plugs
- 3 LED Indicator
LED solid:
normal operation
LED does not light:
1. Possible overload, Unplug
one device and check status
indicator again.
2. Fuse burn-out, please check
the fuse.
- 4 USB-A2/A1 Ports
- 5 USB-C2/C1 Ports

SPECIFICATIONS

- M/N: 652DH
- Single port output mode:
C1+C2: 5.0V=3.0A 15.0W,9.0V=3.0A 27.0W,15.0V=3.0A 45.0W,20.0V=5.0A 100.0W.
A1: 5.0V=3.0A 15.0W,9.0V=2.0A 18.0W,12.0V=1.5A 18.0W.
A2: 5.0V=3.0A 15.0W,9.0V=2.0A 18.0W,12.0V=1.5A 18.0W.
- Combined output mode:
C1+C2 output mode:
C1: 5.0V=3.0A 15.0W,9.0V=3.0A 27.0W,15.0V=3.0A 45.0W,20.0V=3.25A 65.0W.
C2: 5.0V=3.0A 15.0W,9.0V=3.0A 27.0W,15.0V=2.33A 35.0W,20.0V=1.75A 35.0W.
C1+C2+A1 output mode:
C1: 5.0V=3.0A 15.0W,9.0V=3.0A 27.0W,15.0V=3.0A 45.0W,20.0V=3.25A 65.0W.
C2: 5.0V=3.0A 15.0W,9.0V=2.22A 20.0W,12.0V=1.67A 20.0W.
A1: 5.0V=3.0A 15.0W,9.0V=2.0A 18.0W,12.0V=1.5A 18.0W.
C1+C2+A2 output mode:
C1: 5.0V=3.0A 15.0W,9.0V=3.0A 27.0W,15.0V=3.0A 45.0W,20.0V=3.25A 65.0W.
C2: 5.0V=3.0A 15.0W,9.0V=2.22A 20.0W,12.0V=1.67A 20.0W.
A2: 5.0V=3.0A 15.0W,9.0V=2.0A 18.0W,12.0V=1.5A 18.0W.
C1+C2+A1+A2 output mode:
C1: 5.0V=3.0A 15.0W,9.0V=3.0A 27.0W,15.0V=3.0A 45.0W,20.0V=3.25A 65.0W.
C2: 5.0V=3.0A 15.0W,9.0V=2.22A 20.0W,12.0V=1.67A 20.0W.
A1+A2: 5.0V=3.0A 15.0W
- Total DC Output: 100.0W
- Support PD3.0 , QC4+ , FCP , SCP , AFC , PPS , BC1-2 and more
- Dimensions: 93mm x 55mm x 53.5mm
- Operating Temperature: 0°C - 35°C

APPLICABLE OUTLETS


1 Adapter can accept Type A, B, C, E, F, G, I, J, L, N plugs.



Please notice that type D, H, K, M and O plugs are not accepted.



2 Adapter can plug into Type A, B, C, D, E, F, G, H, I, J, K, L, M, N and O outlets.



2-POLE UNEARTHED DEVICES

The product is suitable for use with most electronic devices up to 2500W at 250V and 1000W at 100V. It can be used with a multitude of appliances such as: Laptops, Small travel hair dryers, Travel irons, Electric fan, Table lamp, Electric razors, etc.

Please check the safety data sheet or data plate on the device to find this information before plugging it in.



Laptops



Small travel hair dryers



Travel irons



Electric fan



Table lamp



Electric razors

USB DEVICES

Camera, Smartphone, Tablet, Portable Game Console, Bluetooth speaker, Power bank, etc.



Cameras



Smartphones



Tablets



Portable Game Console



Headsets



Power banks

HOW TO USE THE ADAPTER

Features:

Built-in multi-nation plugs can be selected to fit all outlets in different countries.

Safety function switch ensure only one plug energized.

Attentions:

1. Please make sure that the button is reset when the button is pushed out and retracted to the bottom, and if the button is not reset, it means that the plug has not been pushed in place and will affect the normal use.
2. Only one plug-type can be used at one time by sliding the knob selection, other plug-pins are locked automatically.



USA

Slightly press the button and slide to the down for USA plug completely as shown. make sure the contact blades are turned to the parallel position. Recover the plug: press and hold the "USA" button to release and continue to pull up, until the plug completely pull the top and then release the button, then the button will reset and lock the plug.



Australia / NZ

Slightly press the button and slide to the down for AUS plug completely as shown .make sure the contact blades are turned to the parallel position.

Recover the plug: press and hold the "AUST" button to release and continue to pull up, until the plug completely pull the top and then release the button, then the button will reset and lock the plug.



United Kingdom

Slightly press the button and slide to the down for UK plug completely as shown .Pull out the insulated ground pin from the housing.

Recover the plug: press and hold the "UK" button to release and continue to pull up, until the plug completely pull the top and then release the button, then the button will reset and lock the plug.




EUROPE

Slightly press the button and slide to the down for EUROPE plug completely as shown .make sure the contact blades are turned to the parallel position.

Recover the plug: press and hold the "EUROPE" button to release and continue to pull up, until the plug completely pull the top and then release the button, then the button will reset and lock the plug.

REPLACEMENT OF THE FUSE



1. Take out **1**
2. Take out **2**, and put **2** into the original position of **1**, the adapter could work again.
3. You also could change new fuse.
standard: 240Vac 10A,
6.3*25.4mm,BS1362
approved.

Notes:

1. You should remove all the device before you change the new fuse.
2. Please confirm whether there are water flowed out from the access equipment in the power rating.
3. Please confirm whether the product is wet and there is water flowed out.

CAUTION

- Always disconnect Adapter from the outlet when not in use.
- Before use, please read this instruction carefully! This product does not convert voltage(AC-AC), in order to avoid possible damage to your device or other safety hazards, please make sure the power outlet you intend to use has the proper voltage to run your device before using this adapter.
- Indoor use only.
- Misuse can lead to electrical shock.
- The length of the USB cable should be less than 3M.
- The travel adaptor is for temporary use only and that it shall not be used permanently.
- Against inserting an adaptor into another adaptor shall be provided by the manufacturer.
- No grounding, This product is for use with unearthed or double insulated appliances only.



Waste electrical products should not be disposed of with household waste.
Please recycle where facilities exist.
Check with your Local Authority for recycling advice.



COMPATIBLE COUNTRIES

EU PLUG:

- A** Albania
- Algeria
- Angola
- Argentina
- Austria
- Azores
- B** Balearic Islands
- Bangladesh
- Belgium
- Bolivia
- Bosnia
- Brazil
- Bulgaria
- Burkina Faso
- Burundi
- C** Cameroon
- Canary Island
- Cape Verde
- Central African Republic
- Channel Islands
- Chile
- Comoros
- Congo
- Croatia
- Cote d' Ivoire
- Cyprus
- D** Denmark
- Djibouti
- E** Egypt
- El Salvador
- Equatorial Guinea
- Eritrea
- Faeroe Islands
- Finland
- France
- G** Gabon
- Germany
- Gibraltar
- Greece
- Greenland
- Guadeloupe
- Guinea
- Guinea-Bissau
- H** Hungary
- I** Iceland
- India
- Indonesia
- Iran
- Iraq
- Israel
- Italy
- K** Kazakhstan
- Korea
- Kuwait
- L** Laos
- Lebanon
- Lithuania
- Luxembourg
- M** Macedonia
- Madagascar
- Madeira
- Mali
- Martinique
- Mauritania
- Mauritius
- Monaco
- Morocco

Mozambique

Myanmar

N Nepal

Netherlands

Niger

Norway

O Oman

P Pakistan

Paraguay

Peru

Philippines

Poland

Portugal

R Romania

Russia

Rwanda

S Senegal

Somalia

Spain

Sudan

Suriname

Sweden

Switzerland

Syria

T Thailand

Togo

Tunisia

Turkey

U Uruguay

V Vietnam

Z Zambia

AUS PLUG:

A American Samoa

Argentina

Australia

C China

E El Salvador

F Fiji

G Guatemala

K Kiribati

N Nauru

New Zealand

P Panama

Papua New Guinea

S St. Vincent

T Tajikistan

Tonga

U Uruguay

USA PLUG:

A American Samoa

Anguilla

Antilles

Aruba

B Bahamas

Bangladesh

Barbados

Bermuda

Bolivia

Brazil

C Cambodia

Canada

Cayman Islands

China

Colombia

Costa Rica

Cuba

E Ecuador

El Salvador

G Guam

Guatemala

Guyana

H Haiti

Honduras

J Japan
Jamaica
L Laos
Lebanon
Liberia
M Maldives
Mexico
Micronesia
Montserrat
N Netherlands
Nicaragua
Niger
O Okinawa
P Panama
Peru
Philippines
Puerto Rico
S St. Vincent
Saudi Arabia
T Tahiti
Taiwan
Thailand
United States
V Venezuela
Vietnam
Virgin Islands(US&British)

Y Yemen

UK PLUG:

B Bahrain
Bangladesh
Belize
Botswana
Brunei
C Cameroon
Channel Islands
Cyprus
D Dominica
E El Salvador
G Gambia
Ghana
Gibraltar
Grenada
Guatemala
Guyana
H Hong Kong
I Iraq
Ireland
Isle of Man
J Jordan
K Kuwait
L Lebanon

M Macau
Malawi
Malaysia
Maldives
Malta
Mauritius
Myanmar
N Nigeria
Q Qman
Qatar
S St. Lucia
St. Vincent
Saudi Arabia
Seychelles
Sierra Leone
Singapore
T Tanzania
U Uganda
United Arab Emirates
United Kingdom
V Vietnam
Y Yemen
Z Zambia
Zimbabwe



شاحن عالمي بقدره ٤ منافذ من نوع GAN متوافق في أكثر من ١٥٠ دولة.

MODEL: P100WPDBK


نظرة عامة على المنتج

١. مقاييس متعددة الأقطاب
٢. مقاييس الولايات المتحدة /
أستراليا / ٣. المملكة المتحدة /
الاتحاد الأوروبي

مؤشر LED
LED ثابت:
التشغيل العادي
عدم إضاءة LED:

١. احتمالية حدوث حمل زائد، قم
بفصل جهاز واحد وتحقق من حالة
المؤشر مرة أخرى.
٢. حرق الصمام الكهربائي، يرجى
التحقق من الصمام الكهربائي.

٤. منافذ USB-A
٥. منافذ USB-C



المآخذ المعمول بها

1. يمكن للمحول قبول القابس من النوع A و L و G و I و G و F و G و E و C و B و G و A.

1



Type A Type B Type C Type E Type F Type G Type I Type J Type L Type N

يرجى ملاحظة أن القابس من النوع D و H و K و M و O غير مقبول.



Type D Type H Type K Type M Type O

2. يمكن توصيل المحول بمنافذ النوع A و L و G و M و L و K و G و I و G و H و G و F و G و E و D و C و B و G و A.

2



Type A Type B Type C Type D Type E Type F Type G Type H



Type I Type J Type K Type L Type M Type N Type O

٢- الأجهزة غير المؤرّضة ذات القطبين

المنتج مناسب للاستخدام مع معظم الأجهزة الإلكترونية بقدرته تصل إلى ٢٥٠٠ واط عند ٢٥٠ فولت و ١٠٠٠ واط عند ١٠٠ فولت. يمكن استخدامه مع العديد من الأجهزة مثل الأجهزة المحمولة ومجففات الشعر الصغيرة للسفر ومكواة السفر والمروحة الكهربائية ومصباح الطاولة وماكينات الحلاقة الكهربائية وغيرها. يرجى التحقق من ورقة بيانات السلامة أو لوحة البيانات على الجهاز للعثور على هذه المعلومات قبل توصيله.



أجهزة الكمبيوتر المحمولة



مجففات الشعر الصغيرة للسفر



المروحة الكهربائية



مكواة السفر



مصباح الطاولة



ماكينات الحلاقة الكهربائية

أجهزة USB:

كاميرا، هاتف ذكي، جهاز لوحي، جهاز لعب محمول، مكبر صوت بلوتوث، باور بانك، إلخ.



أجهزة محمولة للألعاب



كاميرات



هواتف ذكية



أجهزة لوحية سماعات الرأس



باوربانك



وحدة تحكم

كيفية استخدام المحول:

الميزات:

يحتوي على قابس متعدد الدول يمكن اختياره لتناسب مع جميع المنافذ في البلدان المختلفة.
يوجد مفتاح وظيفية السلامة لضمان تفعيل قابس واحد فقط.

تنبيهات:

1. يرجى التأكد من إعادة ضبط الزر عند دفعه وسحبه حتى القاعدة، إذا لم يتم إعادة ضبط الزر، فهذا يعني أن القابس لم يتم دفعه بشكل صحيح وسيؤثر على الاستخدام الطبيعي.
2. يمكن استخدام نوع واحد من القابس في وقت واحد عن طريق تحريك مفتاح الاختيار، حيث يتم قفل أقطاب القابس الأخرى تلقائيًا.

اضغط برفق على الزر وانزله تمامًا لت تركيب قابس الولايات المتحدة كما هو موضح. تأكد من أن شفرات الاتصال موجهة بشكل مواز.
لإزالة القابس: اضغط واستمر في الضغط على زر "USA" للإفراج عنه واستمر في سحبه لأعلى حتى ينزلق القابس تمامًا إلى الأعلى، ثم أفلت الزر وسيتم إعادة ضبطه وتأمين القابس.



USA

اضغط برفق على الزر وانزله تمامًا لتثبيت قابس استراليا كما هو موضح. تأكد من أن شفرات الاتصال موجهة بشكل مواز لإزالة القابس: اضغط واستمر في الضغط على زر "AUST" للإفراج عنه واستمر في سحبه لأعلى حتى ينزلق القابس تمامًا إلى الأعلى، ثم أفلت الزر وسيتم إعادة ضبطه وتأمين القابس.



أستراليا / نيوزيلندا

اضغط برفق على الزر وانزله تمامًا لتثبيت قابس المملكة المتحدة كما هو مبين. اسحب دبوس الأرضية المعزولة من الجزء الخارجي للقابس.



المملكة المتحدة

لإعادة تركيب القابس: اضغط واستمر في الضغط على زر "UK" للإفراج عنه واستمر في سحبه لأعلى حتى يتم إزالة القابس تمامًا من الجهة العلوية، ثم أفلت الزر وسيتم إعادة تعيينه وتأمين القابس.

اضغط برفق على الزر وانزله تمامًا لتثبيت قابس أوروبا كما هو مبين. تأكد من أن شفرات الاتصال موجهة في وضع متوازي.


لإعادة تركيب القابس: اضغط واستمر في الضغط على زر "EUROPE" للإفراج عنه واستمر في سحبه لأعلى حتى يتم إزالة القابس تمامًا من الجهة العلوية، ثم أفلت الزر وسيتم إعادة تعيينه وتأمين القابس.



أوروبا

استبدال الصمامة (الفيوز)

١. قم بإخراجها.
٢. قم بإخراجها ووضعا في الموضع الأصلي للمحول ، سيعمل المحول مرة أخرى.
٣. يمكنك أيضا استبدال الصمامة (الفيوز) القديمة بجديدة.
المعايير: ٢٤٠Vac -١.٨A + ٦٣ * ٢٥.٤ مم
معتمدة من قبل ٣٦٢ asl. الترجمة للعربية



ملاحظات:

١. يجب عليك إزالة جميع الأجهزة قبل تغيير الصمامة (الفيوز) الجديدة.
٢. يرجى التأكد مما إذا كان هناك تسرب للماء من الجهاز الموصول في القدرة الكهربائية.
٣. يرجى التأكد مما إذا كان المنتج مبلتا وهناك تسرب للماء. الترجمة للعربية

تنبيه

- قم دائماً بفصل المحول عن مأخذ الطاقة عند عدم الاستخدام.
- قبل الاستخدام، يرجى قراءة هذا التعليمات بعناية! هذا المنتج لا يحول الجهد (تيار متردد إلى تيار متردد)، وذلك من أجل تجنب حدوث أي ضرر لجهازك أو لخلق مخاطر أمنية أخرى.
- يرجى التأكد من أن مأخذ الطاقة الذي تنوي استخدامه يحتوي على الجهد المناسب لتشغيل جهازك قبل استخدام هذا المحول.
- لاستخدام داخلي فقط.
- سوء الاستخدام يمكن أن يؤدي إلى صدمة كهربائية.
- يجب أن يكون طول كابل USB أقل من 3 أمتار.
- المحول السفري للاستخدام المؤقت فقط ولا يجب استخدامه بشكل دائم.
- يجب أن يوفر الشركة المصنعة حماية ضد إدخال محول في محول آخر.
- لا يتوفر تاريض، يجب استخدام هذا المنتج مع الأجهزة غير المؤرضة أو ذات العزل المزدوج فقط. الترجمة للعربية.

لا يجب التخلص من المنتجات الكهربائية القديمة مع النفايات المنزلية.
يرجى إعادة التدوير إذا توفرت المرافق المناسبة.
تتفق مع السلطة المحلية للحصول على نصائح حول إعادة التدوير.
الترجمة للعربية



البلدان المتوافقة

قابس الاتحاد الأوروبي

A Albania
Algeria
Angola
Argentina
Austria
Azores
B Balearic Islands
Bangladesh
Belgium
Bolivia
Bosnia
Brazil
Bulgaria
Burkina Faso
Burundi
C Cameroon
Canary Island
Cape Verde
Central African Republic
Channel Islands
Chile

Comoros
Congo
Croatia
Cote d' Ivoire
Cyprus
D Denmark
Djibouti
E Egypt
El Salvador
Equatorial Guinea
Eritrea
Faeroe Islands
Finland
France

G Gabon
Germany
Gibraltar
Greece
Greenland
Guadeloupe
Guinea
Guinea-Bissau

H Hungary

I Iceland
India
Indonesia
Iran
Iraq
Israel
Italy
K Kazakhstan
Korea
Kuwait
L Laos
Lebanon
Lithuania
Luxembourg
M Macedonia
Madagascar
Madeira
Mali
Martinique
Mauritania
Mauritius
Monaco
Morocco

Mozambique

Myanmar

N Nepal

Netherlands

Niger

Norway

O Oman

P Pakistan

Paraguay

Peru

Philippines

Poland

Portugal

R Romania

Russia

Rwanda

S Senegal

Somalia

Spain

Sudan

Suriname

Sweden

Switzerland

Syria

T Thailand

Togo

Tunisia

Turkey

U Uruguay

V Vietnam

Z Zambia

AUS PLUG:

A American Samoa

Argentina

Australia

C China

E El Salvador

F Fiji

G Guatemala

K Kiribati

N Nauru

New Zealand

P Panama

Papua New Guinea

S St. Vincent

T Tajikistan

Tonga

U Uruguay

USA PLUG:

A American Samoa

Anguilla

Antilles

Aruba

B Bahamas

Bangladesh

Barbados

Bermuda

Bolivia

Brazil

C Cambodia

Canada

Cayman Islands

China

Colombia

Costa Rica

Cuba

E Ecuador

El Salvador

G Guam

Guatemala

Guyana

H Haiti

Honduras

J Japan
Jamaica

L Laos
Lebanon
Liberia

M Maldives
Mexico
Micronesia
Montserrat

N Netherlands
Nicaragua
Niger

O Okinawa

P Panama
Peru
Philippines
Puerto Rico

S St. Vincent
Saudi Arabia

T Tahiti
Taiwan
Thailand
United States

V Venezuela
Vietnam
Virgin Islands(US&British)

Y Yemen

UK PLUG:

B Bahrain
Bangladesh
Belize
Botswana
Brunei

C Cameroon
Channel Islands
Cyprus

D Dominica

E El Salvador

G Gambia
Ghana
Gibraltar
Grenada
Guatemala
Guyana

H Hong Kong

I Iraq
Ireland
Isle of Man

J Jordan

K Kuwait

L Lebanon

M Macau
Malawi
Malaysia
Maldives
Malta
Mauritius
Myanmar

N Nigeria

Q Qman
Qatar

S St. Lucia
St. Vincent
Saudi Arabia
Seychelles
Sierra Leone
Singapore

T Tanzania

U Uganda
United Arab Emirates
United Kingdom

V Vietnam

Y Yemen

Z Zambia
Zimbabwe